

TOTAL MEMORY	BANK 0 (30-PIN)	BANK 1 (72-PIN)	BANK 2 (72-PIN)
80MB	16MB x 4	16MB x 1	
	16MB x 4		16MB x 1
81MB	16MB x 4	1MB x 1	16MB x 1
	16MB x 4	16MB x 1	1MB x 1
84MB	16MB x 4	4MB x 1	16MB x 1
	16MB x 4	16MB x 1	4MB x 1
96MB	16MB x 4	16MB x 1	16MB x 1

Table 3-1. DRAM Configurations

→ **NOTE :** When using double-RAS SIMMs, it is advised that Bank 2 be used instead of Bank 1 and both cannot contain double-RAS SIMM at the same time. If Bank 1 contains a double-RAS SIMM, then Bank 0 (30-pin) is rendered inoperative.

Installation Instructions

→ **NOTE :** Always observe static electricity precautions. See "Handling Precautions" at the start of this manual.

1. Locate the SIMM banks on the mainboard. Determine your desired configuration to be installed.
2. Insert the SIMM edge connector at a 90-degree angle onto the socket.




Figure 3-2. Installing SIMMs